R8-ZERO Bluetooth Smart Mortise Door Lock

- An aesthetic design adds style to enhance household quality.
- Unlock the lock without exposing the user code by smart phone access, enter your home quickly and safely.
- The door locks automatically, ensure safety every time you leave.
- Available for ANSI & EN mortise locket.

ANSI Mortise Lock

- US ANSI Grade 1
- UL 10C 3 hours fire rating



EN Mortise Lock

- EN 179:2008 Emergency exit
- EN 1634-1:2004 Fire rated up to 4 hours.
- EN 12209:2003/ AC:2005 -Building hardware. Lock and latch. Mechanically lock, latch, and locking plate.
- EN14846:2008 Building hardware. Lock and latch. Electromechanically operated lock, latch, and locking plate.









Multiple Access

· Bluetooth, PIN Code, Card and Key Override.





Download KevLok from App Store or Google Play.

Touch Keypad

- Responsive touch keypad.
- Random code technology to prevent from peeking.
- LED backlit for convenient operation at night.

Two Administration Modes

- EZ mode
 - 1.ONE user code is available.
 - 2.One-time user code is not available.
 - 3. Keypad sound cannot be turned off.
- Normal mode
 - 1.Maximum 200 user codes.
 - 2.One-time user code is available.

SPECIFICATIONS

Card Compatibility	Mifare 13.56MHz / ISO 14443A
Capacity	200 users (use codes & cards)
Card Reading Distance	20 to 30 mm
Lockset Options	ANSI mortise lock (option) EN mortise lock (option)
Finish	US26D, US32D

Door Thickness	40 to 80 mm
Backset	70 mm (ANSI mortise lockset) 60 mm (EN mortise lockset)
Power Supply	4 AA alkaline 1.5V batteries (6V)
Battery Life	up to 12 months
Working Temperature	-20°C to 70°C (-4°F to 158°F)





Hold Open Mode

• The lock can be set between 1 to 999 minutes to remain unlocked when people need to go in and out consistently.

Prank Warning

• The touch keypad will be disabled after entering 10 times of incorrect user codes consecutively to prevent trespassing.

Emergency Power Supply

• When batteries are completely dead, use a type C cable to temporarily power up the lock.

Low Battery Warning

• If the batteries are running low, the door lock informs you through keypad with a digit for entry times left, also beep and blink * 3 times.

3. Keypad sound can be turned off.